

Underlay P/N: 601-2600-05

Model Description: Millennium2005

Telephone P/N: 00G4100-005

# Millennium2005 CUSTOM FACEPLATE WORKSHEET

Date: \_\_\_\_\_

Contact: \_\_\_\_\_

Company: \_\_\_\_\_

Tel No: \_\_\_\_\_

Fax No: \_\_\_\_\_

PO #: \_\_\_\_\_ Date Required: \_\_\_\_\_

End user: \_\_\_\_\_

Address: \_\_\_\_\_

Tel No: \_\_\_\_\_

Fax No: \_\_\_\_\_

## Specifications

Paper Color: \_\_\_\_\_

Ink Color: \_\_\_\_\_

Quantity: \_\_\_\_\_

## Comments / Instructions

- Note** 1. Please verify that your telephone P/N and description match those referenced above.  
 2. Please include pre-programming information when applicable.

Text shown is default for Redial, Volume, Mute, Hold, Line1 / Line2, Conf and Speaker keys. Any change from the default must be noted.



D  
A  
T  
A

The diagram shows a telephone keypad faceplate layout. At the top, there are five small rectangular buttons labeled 1 through 5. Below these is a standard 12-button numeric keypad. The buttons are arranged as follows:

- Row 1: 1, 2 ABC, 3 DEF, Hold
- Row 2: 4 GHI, 5 JKL, 6 MNO, Redial
- Row 3: 7 PRS, 8 TUV, 9 WXY, Mute
- Row 4: \*, 0 OPER, #, Conference
- Row 5: - Volume +, Line 1, Line 2, Speaker

Each button is represented by a rounded rectangle with its label inside. The 'Hold', 'Redial', 'Mute', and 'Conference' buttons have a small square icon to their right. The 'Line 1', 'Line 2', and 'Speaker' buttons have a small square icon above them. The 'Volume' control is represented by a horizontal oval with a vertical line through it and minus/plus signs on either side.

Scale: 1:1